H25 Series TUBULAR MOTOR



Drive Shaft


Square Limit Head

Application

External AC power supply power to motor, suitable for the application with the convenient power connection, no need to connect the outside receiver, has a simple and clear install environment.




External AC power supply power to motor, can be controlled by wireless remote and smart home devices to realize the group control function.





IH25 built-in power supply tubular motor mainly used for interior small size alumium and wooden venetian blinds honeycomb blinds etc. With built in receiver, Saves space and builds beauty installation. Also compatible with all A-OK intelligent controllers, bring your office, metting room, house convenient experiences.

Standard Limit Head



Features

- Bi-voltage power supply for global market
- Available for 6 limits
- ✤ Quiet running with noise level below 40dB
- To set limit by remote, simplify your installation and operation Stock on block function to protect whole system
- Auto-check running turns to accurate the limits
- * Industry level electronic components ensure good performance from interference working environment, sensitivity is -110dBm
- ♦ Auto correct limit after power off



Parameters

Model No.	Rated Torque	Rated RPM	Motor Diameter	Rated Voltage	Rated Power	Rated Current	IP Class
IH25-1.2/30-ES-E	1.2N.m	30rpm	25mm	DC7.4V	6.7W	900mA	IP44
IH25-1.2/30-E	1.2N.m	30rpm	25mm	230V	36W	0.485A	IP44

H25 Series TUBULAR MOTOR

